

EN - Safety instructions - Installation instructions

Olympus EI

1- Installation and commissioning may only be carried out by authorized specialists. Plaster housing should be installed by the false ceiling installer. Electrical components must be connected by qualified electrician.

2- BEWARE! Make sure the luminaires are always disconnected from the mains supply during wiring, installation and maintenance work. Before starting the installation, make sure the power is switched off.

3- This fixture is suitable for indoor use only (not suitable for wet area). The luminaire is exclusively used for lighting and is to be installed in accordance with the national regulations. Any other use or installation is regarded as "non according to instructions".

4- The luminaire with F mark are suitable for installation on normally flammable surfaces.

5- Always be sure to keep a minimum spacing of more than 0.5m (50cm) between the luminaire and the illuminated surface.

6- Do not cover the luminaire. Be really careful with insulating material. Avoid excess of dust deposition over the luminaire.

7- Ceiling installation only:

Make a **circular hole** in the ceiling according to table below.

Olympus EI			
Code	Cut Out Dimension mm	Code	Cut Out Dimension mm
1002 EL	$\phi = 190$	1090 EL EM	$\phi = 225$
1084 EL	$\phi = 225$	1006 EL	$\phi = 260$
1086 EL	$\phi = 225$	1006 EL DIM	$\phi = 260$
1086 EL DIM	$\phi = 225$	1006 EL EM	$\phi = 260$
1086 EL EM	$\phi = 225$	1031 EL	$\phi = 260$
1004 EL	$\phi = 225$	1033 EL	$\phi = 260$
1090 EL	$\phi = 225$	1032 EL	$\phi = 260$
1090 EL DIM	$\phi = 225$	1034 EL	$\phi = 260$

Take the mains cable and pass it through the hole.


Connect the mains cable to the terminal block of the luminaire.

Pass the cable in the cable clamp and screw it tight.

8- Insert the luminaire in the hole in the ceiling

9- Place / replace the lamp HIT-CE G8.5 20W or 35W

Protection class I. The ground cable (green/yellow) must be connected. If there is not a mains supply with a protective ground wire available, the product must not be connected /used there.



KEEP THESE INSTRUCTIONS
FOR FURTHER REFERENCE.